

L83-XAF5

L83 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Fr 500, 1000, 2000, 5000, 10000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Fr 500	OFF	OFF	OFF								
	2 Pulse / Fr 500	OFF	OFF	ON								
	5 Pulse / Fr 500	OFF	ON	OFF								
	10 Pulse / Fr 500	OFF	ON	ON								
	20 Pulse / Fr 500	ON	OFF	OFF								
	50 Pulse / Fr 500	ON	OFF	ON								
	100 Pulse / Fr 500	ON	ON	OFF								
	200 Pulse / Fr 500	ON	ON	ON								
★	Fast output Pulse Lo= 50ms Hi=100ms				ON							
	Slow output Pulse Lo= 50ms Hi=300ms				OFF							
	Inhibit level Active Low					ON						
★	Inhibit level Active High					OFF						
★	Accept Fr 500						ON					
	Reject Fr 500						OFF					
★	Accept Fr 1000								ON			
	Reject Fr 1000								OFF			
★	Accept Fr 2000									ON		
	Reject Fr 2000									OFF		
★	Accept Fr 5000										ON	
	Reject Fr 5000										OFF	
★	Accept Fr 10000											ON
	Reject Fr 10000											OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104 Protocol Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	Fr 500	Fr 500
BV2	Fr 1000	Fr 1000
BV3	Fr 2000	Fr 2000
BV4	Fr 5000	Fr 5000
BV5	Fr 10000	Fr 10000