

NE77-PLN5

NE77 DIP SWITCHES SETTING : (Pulse/Parallel A4/ccTalk)

Supported bill PLN 10, 20, 50, 100, 200 5bills.

DIP SWITCHES SETTING : (Parallel A4)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	WITH ESCOW FUNCTION	ON									
★	NO ESCOW FUNCTION	OFF									
	ccTalk Potocol		ON								
★	Parallel A4 Potocol		OFF								
	Reserved			ON							
★	Reserved			OFF							
★	Enable Output Sensor Detect				ON						
	Disable Output Sensor Detect				OFF						
	Reserved				ON						
★	Reserved				OFF						
	Optical anti-fishing malfunction, BA will be still in working order					ON					
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction					OFF					
★	Accept PLN 10 & 20							ON			
	Reject PLN 10 & 20							OFF			
★	Accept PLN 50 & 100 & 200							ON			
	Reject PLN 50 & 100 & 200							OFF			
	Disable Bill Reject 4 Times BA Stop By 30 Sec								ON		
★	Enable Bill Reject 4 Times BA Stop By 30 Sec								OFF		
	Pulse Protocol									ON	
★	Other Protocol									OFF	

★ Manufacture setting

Note1 : Please restart the bill acceptor after any changes on dip switch(s) has been made.

Note2 : Turn this dip to with restart the bill acceptor will restore
ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Currency Assign Data

Interface Bill value	Pulse	Parallel A4	ccTalk
BV1	PLN 10	PLN 10	PLN 10
BV2	PLN 20	PLN 20	PLN 20
BV3	PLN 50	PLN 50	PLN 50
BV4	PLN 100	PLN 100	PLN 100
BV5	PLN 200	PLN 200	PLN 200

NE77 - PLN5 (Pulse/Parallel A4/ccTalk)

DIP SWITCHES SETTING : (Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	10 Pulses / PLN 10	ON									
★	1 Pulse / PLN 10	OFF									
★	Lo=150ms / Hi=180ms		OFF	OFF							
	Lo=100ms / Hi=100ms		OFF	ON							
	Lo= 50ms / Hi=100ms		ON	OFF							
	Lo= 50ms / Hi= 50ms		ON	ON							
★	Enable Output Sensor Detect				ON						
	Disable Output Sensor Detect				OFF						
	Inhibit level Active High					ON					
★	Inhibit level Active Low					OFF					
	Optical anti-fishing malfunction, BA will be still in working order						ON				
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction						OFF				
★	Accept PLN 10 & 20							ON			
	Reject PLN 10 & 20							OFF			
★	Accept PLN 50 & 100 & 200								ON		
	Reject PLN 50 & 100 & 200								OFF		
	Disable Bill Reject 4 Times BA Stop By 30 Sec									ON	
★	Enable Bill Reject 4 Times BA Stop By 30 Sec									OFF	
★	Pulse Protocol										ON
	Other Protocol										OFF

DIP SWITCHES SETTING : (ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	Reserved	ON									
★	Reserved	OFF									
★	ccTalk Protocol		ON								
	Parallel A4 Protocol		OFF								
★	Encryption MODE			ON							
	Decrypt MODE			OFF							
★	Enable Output Sensor Detect				ON						
	Disable Output Sensor Detect				OFF						
	ccTalk parameters restore (Please see Note.2 for detail)					ON					
★	ccTalk parameters not restore					OFF					
	Optical anti-fishing malfunction, BA will be still in working order						ON				
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction						OFF				
★	Accept PLN 10 & 20							ON			
	Reject PLN 10 & 20							OFF			
★	Accept PLN 50 & 100 & 200								ON		
	Reject PLN 50 & 100 & 200								OFF		
	Disable Bill Reject 4 Times BA Stop By 30 Sec									ON	
★	Enable Bill Reject 4 Times BA Stop By 30 Sec									OFF	
	Pulse Protocol										ON
★	Other Protocol										OFF