

NK77-KRW4

NK77 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill KRW 1000, 5000, 10000, 50000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / KRW 1000	OFF	OFF								
	5 Pulses / KRW 1000	ON	OFF								
	10 Pulses / KRW 1000	OFF	ON								
	15 Pulses / KRW 1000	ON	ON								
★	Accept KRW 1000			ON							
	Reject KRW 1000			OFF							
★	Accept KRW 5000				ON						
	Reject KRW 5000				OFF						
★	Accept KRW 10000					ON					
	Reject KRW 10000					OFF					
★	Accept KRW 50000						ON				
	Reject KRW 50000						OFF				
★	Enable Output Sensor Detect							ON			
	Disable Output Sensor Detect							OFF			
	Fast output Pulse Lo= 50ms Hi=100ms								ON		
★	Slow output Pulse Lo=100ms Hi=200ms								OFF		
★	Pulse Mode									ON	
	ICT104U Mode									OFF	
	Reserved										ON
★	Reserved										OFF

(★) Manufacture setting

Note : Please reset the bill acceptor after set the dip switch.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	KRW 1000	KRW 1000
BV2	KRW 5000	KRW 5000
BV3	KRW 10000	KRW 10000
BV4	KRW 50000	KRW 50000