

NK77-KRW4

NK77 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill ₩ 1000, 5000, 10000, 50000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10						
★	1 Pulse τ W 1000	OFF	OFF														
	2 Pulses τ W 1000	ON	OFF														
	5 Pulses τ W 1000	OFF	ON														
	10 Pulses τ W 1000	ON	ON														
★	Accept τ W 1000			ON													
	Reject τ W 1000			OFF													
★	Accept τ W 5000				ON												
	Reject τ W 5000				OFF												
★	Accept τ W 10000					ON											
	Reject τ W 10000					OFF											
★	Accept τ W 50000						ON										
	Reject τ W 50000						OFF										
★	Enable Output Sensor Detect							ON									
	Disable Output Sensor Detect							OFF									
★	Fast output Pulse Lo= 50ms Hi =100ms								ON								
	Slow output Pulse Lo=100ms Hi =200ms								OFF								
★	Pulse Mode									ON							
	ICT104U Mode									OFF							
	Manufacture Default										ON						
★	System Default										OFF						

(★) Manufacture setting

Note : Please reset the bill acceptor after set the dip switch.

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	1000	1000
BV2	5000	5000
BV3	10000	10000
BV4	50000	50000