

## NK77-THB4

### NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT10A)

**Supported bill THB 20, 50, 100, 500 4bills.**

|   | FUNCTION                     | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|---|------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / THB 10             | OFF | OFF |     |     |     |     |     |     |     |      |
|   | 2 Pulse / THB 10             | OFF | ON  |     |     |     |     |     |     |     |      |
|   | 5 Pulse / THB 10             | ON  | OFF |     |     |     |     |     |     |     |      |
|   | 10 Pulse / THB 10            | ON  | ON  |     |     |     |     |     |     |     |      |
| ★ | Enable Fish Stop             |     |     | ON  |     |     |     |     |     |     |      |
|   | Disable Fish Stop            |     |     | OFF |     |     |     |     |     |     |      |
| ★ | Inhibit level Active Low     |     |     |     | ON  |     |     |     |     |     |      |
|   | Inhibit level Active High    |     |     |     | OFF |     |     |     |     |     |      |
| ★ | Accept THB 20 & 50 & 100     |     |     |     |     | ON  |     |     |     |     |      |
|   | Reject THB 20 & 50 & 100     |     |     |     |     | OFF |     |     |     |     |      |
| ★ | Accept THB 500               |     |     |     |     |     | ON  |     |     |     |      |
|   | Reject THB 500               |     |     |     |     |     | OFF |     |     |     |      |
| ★ | Enable Output Sensor Detect  |     |     |     |     |     |     | ON  |     |     |      |
|   | Disable Output Sensor Detect |     |     |     |     |     |     | OFF |     |     |      |
| ★ | Pulse Normal High            |     |     |     |     |     |     |     | ON  |     |      |
|   | Pulse Normal Low             |     |     |     |     |     |     |     | OFF |     |      |
| ★ | Pulse Mode                   |     |     |     |     |     |     |     |     | ON  |      |
|   | ICT10A Mode                  |     |     |     |     |     |     |     |     | OFF |      |
| ★ | Power On Motor Plus          |     |     |     |     |     |     |     |     |     | ON   |
|   | Power On Motor Minus         |     |     |     |     |     |     |     |     |     | OFF  |

(★) Manufacture setting

### **Currency Assign Data**

| Interface<br>Bill value | ICT     | Pulse   |
|-------------------------|---------|---------|
| BV1                     | THB 20  | THB 20  |
| BV2                     | THB 50  | THB 50  |
| BV3                     | THB 100 | THB 100 |
| BV4                     | THB 500 | THB 500 |

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Pulse mode has out of service function.

(3) Out of service: Normal High, Error Low.

(4) Pulse speed is LO=50ms/HI=100ms