NK77-THB4

NK77 DIP SWITCHES SETTING: (Pulse/Out of Service/ICT104U) Supported bill THB 20, 50, 100, 500 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
*	1 Pulse / THB 10	OFF	OFF								
	2 Pulse / THB 10	OFF	ON								
	5 Pulse / THB 10	ON	OFF								
	10 Pulse / THB 10	ON	ON								
	Enable Fish Stop			ON							
*	Disable Fish Stop			OFF							
*	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
*	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
*	Accept THB 500						ON				
	Reject THB 500						OFF				
	Enable Output Sensor Detect							ON			
*	Disable Output Sensor Detect							OFF			
*	Pluse Normal High								ON		
	Pluse Normal Low								OFF		
*	Pulse Mode									ON	
	ICT104U Mode									OFF	
*	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note:1. Please reset the bill acceptor after set the dip switch

- 2. Pulse mode has out of service function
- 3. Out of service:Normal High,Error Low
- 4. Pulse speed is LO=50ms/HI=100ms

Currency Assign Data

Interface Bill value	ICT1	04U	Pulse			
BV1	THB	20	THB	20		
BV2	THB	50	THB	50		
BV3	THB	100	THB	100		
BV4	THB	500	THB	500		



