

A7/V7 Option Switch Settings: 1 (Pulse/ICT)**Supported bill THB 20, 50, 100, 500****4bills.**

A7/V7 dip-switch settings and functions:

| | FUNCTION | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|---|----------------------|----------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ | Reject THB 20 | ON | | | | | | | | | | | |
| ★ | Accept THB 20 | OFF | | | | | | | | | | | |
| | Reject THB 50 | | ON | | | | | | | | | | |
| ★ | Accept THB 50 | | OFF | | | | | | | | | | |
| | Reject THB 100 | | | ON | | | | | | | | | |
| ★ | Accept THB 100 | | | OFF | | | | | | | | | |
| | Reject THB 500 | | | | ON | | | | | | | | |
| ★ | Accept THB 500 | | | | OFF | | | | | | | | |
| | Reserved | | | | ON | | | | | | | | |
| ★ | Reserved | | | | OFF | | | | | | | | |
| | Reserved | | | | | ON | | | | | | | |
| ★ | Reserved | | | | | OFF | | | | | | | |
| | Harness Disable | | | | | | ON | | | | | | |
| ★ | Harness Engble | | | | | | OFF | | | | | | |
| | Inhiblit Active High | | | | | | | ON | | | | | |
| ★ | Inhibit Active Low | | | | | | | OFF | | | | | |
| | 1 pulse / THB 10 | | | | | | | | OFF | OFF | | | |
| ★ | 2 pulse / THB 10 | | | | | | | | ON | OFF | | | |
| | 4 pulse / THB 10 | | | | | | | | OFF | ON | | | |
| ★ | 20 pulse / THB 10 | | | | | | | | ON | ON | | | |
| | Pulse Speed | 50ms on / 50ms off | | | | | | | | | OFF | OFF | |
| ★ | | 60ms on / 300ms off | | | | | | | | | ON | OFF | |
| | | 30ms on / 50ms off | | | | | | | | | OFF | ON | |
| ★ | | 150ms on / 150ms off | | | | | | | | | ON | ON | |

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7 Interface Settings: 2 (ICT)

| | INTERFACE | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal HIGH | ON | | | |
| | Credit-Pulse Normal LOW | OFF | | | |
| ★ | Pulse Mode | | ON | | |
| | ICT Interface | | OFF | | |
| | Reserved | | | ON | |
| ★ | | | | OFF | |
| | | | | | ON |
| ★ | | | | | OFF |

★ Manufacture setting