

P70-VEF6

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Bs 2, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Bs 1	OFF	OFF	OFF							
	2 Pulse / Bs 1	OFF	OFF	ON							
	3 Pulse / Bs 1	OFF	ON	OFF							
	4 Pulse / Bs 1	OFF	ON	ON							
	5 Pulse / Bs 1	ON	OFF	OFF							
	10 Pulse / Bs 1	ON	OFF	ON							
	20 Pulse / Bs 1	ON	ON	OFF							
	100 Pulse / Bs 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Bs 2 & 5				ON						
	Reject Bs 2 & 5				OFF						
★	Accept Bs 10				ON						
	Reject Bs 10				OFF						
★	Accept Bs 20				ON						
	Reject Bs 20				OFF						
★	Accept Bs 50				ON						
	Reject Bs 50				OFF						
★	Accept Bs 100				ON						
	Reject Bs 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	2	2
BV2	5	5
BV3	10	10
BV4	20	20
BV5	50	50
BV6	100	100