

TAO-A.V-VND6

TAO-A.V Option Switch Settings: 1(Pulse/ICT/MDB)

Supported bill VND 1000, 2000, 5000, 10000, 20000, 50000 6bills.

TAO-A.V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject VND 1000	ON											
★ Accept VND 1000	OFF											
★ Reject VND 2000		ON										
★ Accept VND 2000		OFF										
★ Reject VND 5000			ON									
★ Accept VND 5000			OFF									
★ Reject VND 10000				ON								
★ Accept VND 10000				OFF								
★ Reject VND 20000					ON							
★ Accept VND 20000					OFF							
★ Reject VND 50000						ON						
★ Accept VND 50000						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / VND 1000									OFF	OFF		
5 pulses / VND 1000									ON	OFF		
10 pulses / VND 1000									OFF	ON		
20 pulses / VND 1000									ON	ON		
★ Interface Timing Conversion		50ms on / 50ms off									OFF	OFF
		60ms on / 300ms off									ON	OFF
		30ms on / 50ms off									OFF	ON
		150ms on / 150ms off									ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

TAO-A.V-VND6(Pulse/ICT104V/ICT002U/MDB)

Interface Settings: 3(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT002U Interface		OFF	OFF	
MDB Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Interface Settings: 3(ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Not Used	ON			
Not Used	OFF			
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT002U Interface		OFF	OFF	
MDB Interface		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Interface Settings: 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 1	ON			
Decimal Point Position (DPP) = 0				
Scaling Factor (SF) = 1	OFF			
Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT002U Interface		OFF	OFF	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	VND 1000	VND 1000	VND 1000
BV2	VND 2000	VND 2000	VND 2000
BV3	VND 5000	VND 5000	VND 5000
BV4	VND 10000	VND 10000	VND 10000
BV5	VND 20000	VND 20000	VND 20000
BV6	VND 50000	VND 50000	VND 50000