BRV-AUD5

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Supported bill AUD 5, 10, 20, 50, 100 5bills.

BRV dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject AUD 5	ON											
★	Accept AUD 5	OFF											
	Reject AUD 10		ON										
★	Accept AUD 10		OFF										
	Reject AUD 20			ON									
★	Accept AUD 20			OFF									
	Reject AUD 50				ON								
★	Accept AUD 50				OFF								
	Reject AUD 100					ON							
★	Accept AUD 100					OFF							
★	Normal						OFF	OFF					
	Load Banknote to Recycle						ON	OFF					
	Load Banknote to Stacker						OFF	ON					
	Unload Banknote to Stacker						ON	ON					
	Reserved								ON				
★	Reserved								OFF				

	MDB Mode	MDB Dummy Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode				
	Reserved	Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON	
★	Reserved	Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF	
	Reserved	Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF	
★	Reserved	Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF	
	Reserved	Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF	
★	Reserved	Reserved			OFF		5 Bank Note Limitation Per Transaction	OFF	OFF	ON	
	Virtual MDB Recycler Function (Note.4)	No Refund After the Deal				ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON	ON
★	Standard MDB Recycler Function	★ Refund After the Deal				OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON	OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.
(2) Please reset the bill acceptor after set the dip switch.
(3) Calibration card is needed.
(4) Recycled Banknote represents virtual MDB coin type.
(5) Virtual Coin Changer : Scaling Factor = 100, Decimal Point Position = 2.

BRV-AUD5(ICT-BC/MDB/JPSTD Dummy/MDB Dummy)

Interface Settings: 2(ICT-BC)

	INTERFACE	SW5	SW6	SW7	SW8
	Reserved	ON			
★	Reserved	OFF			
	Connect with MDB Connector		ON		
★	Connect with RS232 Connector		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
★	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
	Escrow (JPSTD Dummy Mode)	ON			
★	No Escrow (JPSTD Dummy Mode)	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
★	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW5	SW6	SW7	SW8
★	Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP)= 0	OFF			
	Reserved		ON		
★	Reserved		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
	MDB Dummy Mode			ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB Dummy)

	INTERFACE	SW5	SW6	SW7	SW8
★	Reserved	ON			
	Reserved	OFF			
	Reserved		ON		
★	Reserved		OFF		
	MDB Mode			OFF	OFF
	JPSTD Dummy Mode			OFF	ON
★	MDB Dummy Mode	(Note.5)		ON	OFF
	ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface / Bill value	JPSTD Dummy	ICT-BC	MDB Dummy	Recycler banknote inventory	
BV1	AUD 5	AUD 5	AUD 5	AUD 5	35 pcs
BV2	AUD 10	AUD 10	AUD 10	AUD 10	35 pcs
BV3	AUD 20	AUD 20	AUD 20	AUD 20	35 pcs
BV4	AUD 50	AUD 50	AUD 50	AUD 50	30 pcs
BV5	AUD 100	AUD 100	AUD 100	AUD 100	30 pcs

© 2023 International Currency Technologies Corporation
V. 2.0 Part Number : SWDTAU50200-R