

# BRV-TRY6

## BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill TRY 5, 10, 20, 50, 100, 200 6bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject TRY 5	ON											
★ Accept TRY 5	OFF											
★ Reject TRY 10		ON										
★ Accept TRY 10		OFF										
★ Reject TRY 20			ON									
★ Accept TRY 20			OFF									
★ Reject TRY 50				ON								
★ Accept TRY 50				OFF								
★ Reject TRY 100 & 200					ON							
★ Accept TRY 100 & 200					OFF							
★ Normal						OFF	OFF					
★ Load Banknote to Recycle						ON	OFF					
★ Load Banknote to Stacker						OFF	ON					
★ Unload Banknote to Stacker						ON	ON					
★ Reserved								ON				
★ Reserved								OFF				
<b>MDB Mode</b>	SW1	SW2	SW3	SW4	<b>JPSTD Dummy Mode</b>							
★ Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
★ Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
★ Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
★ Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
★ Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
★ Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
★ Reserved				ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
★ Reserved				OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON				
★ Virtual MDB Recycler Function (Note.3)				ON	No Refund After the Deal							ON
★ Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) Please reset the bill acceptor after set the dip switch.  
 (2) Calibrate card is needed.  
 (3) Recycled Banknote represents virtual MDB coin type.

# BRV-TRY6(ICT-BC/MDB/JPSTD Dummy)

## Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
★ Reserved	OFF			
★ Connect with MDB Connector		ON		
★ Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
★ No Escrow (JPSTD Dummy Mode)	OFF			
Reserved		ON		
★ Reserved		OFF		
MDB Mode			OFF	OFF
★ JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

## Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
★ Scaling Factor (SF)= 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP) = 0	OFF			
Reserved		ON		
★ Reserved		OFF		
★ MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
★ ICT-BC Mode			ON	ON

★ Manufacture setting

## Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	TRY 5	TRY 5	TRY 5	TRY 5	35 pcs
BV2	TRY 10	TRY 10	TRY 10	TRY 10	35 pcs
BV3	TRY 20	TRY 20	TRY 20	TRY 20	35 pcs
BV4	TRY 50	TRY 50	TRY 50	TRY 50	30 pcs
BV5	TRY 100	TRY 100	TRY 100	TRY 100	30 pcs
BV6	TRY 200	TRY 200	TRY 200	TRY 200	30 pcs