

L77F/PL77-JPY4

L77F/PL77 DIP SWITCHES SETTING : 1(Pulse/ICT104U/ICT104V/MDB)

Supported bill JPY 1000, 2000, 5000, 10000 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ¥ 1000	OFF	OFF	OFF							
2 Pulses / ¥ 1000	OFF	OFF	ON							
3 Pulses / ¥ 1000	OFF	ON	OFF							
4 Pulses / ¥ 1000	OFF	ON	ON							
5 Pulses / ¥ 1000	ON	OFF	OFF							
10 Pulses / ¥ 1000	ON	OFF	ON							
20 Pulses / ¥ 1000	ON	ON	OFF							
100 Pulses / ¥ 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept ¥ 1000						ON				
Reject ¥ 1000						OFF				
★ Accept ¥ 2000							ON			
Reject ¥ 2000							OFF			
★ Accept ¥ 5000								ON		
Reject ¥ 5000								OFF		
★ Accept ¥ 10000									ON	
Reject ¥ 10000									OFF	
Accept only new JPY(2024)										ON
★ Accept all JPY										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

(3)Scaling Factor (SF) = 1,Decimal Point Position (DPP) = 0

L77F&PL77-JPY4(Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
Reserved	ON			
★	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	Pulse	MDB
BV1	¥ 1000	¥ 1000	¥ 1000	¥ 1000
BV2	¥ 2000	¥ 2000	¥ 2000	¥ 2000
BV3	¥ 5000	¥ 5000	¥ 5000	¥ 5000
BV4	¥10000	¥10000	¥10000	¥10000

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
Reserved				ON
★				OFF

★ Manufacture setting