

L77F/PL77-RUB7

L77F/PL77 Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill RUB 5, 10, 50, 100, 200, 500, 1000 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / RUB 5 or 10 or 50(No.3)	OFF	OFF	OFF							
2 Pulses / RUB 5 or 10 or 50(No.3)	OFF	OFF	ON							
3 Pulses / RUB 5 or 10 or 50(No.3)	OFF	ON	OFF							
4 Pulses / RUB 5 or 10 or 50(No.3)	OFF	ON	ON							
5 Pulses / RUB 5 or 10 or 50(No.3)	ON	OFF	OFF							
10 Pulses / RUB 5 or 10 or 50(No.3)	ON	OFF	ON							
20 Pulses / RUB 5 or 10 or 50(No.3)	ON	ON	OFF							
100 Pulses / RUB 5 or 10 or 50(No.3)	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept RUB 5						ON				
Reject RUB 5						OFF				
★ Accept RUB 10							ON			
Reject RUB 10							OFF			
★ Accept RUB 50 & 100								ON		
Reject RUB 50 & 100								OFF		
★ Accept RUB 200									ON	
Reject RUB 200									OFF	
★ Accept RUB 500 & 1000										ON
Reject RUB 500 & 1000										OFF

★ Manufacture setting

- Note: (1) Please reset the bill acceptor after any changes on Dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.
 (3) Pulse mode: Accept RUB 5 ==> 1 Pulse / RUB 5
 Reject RUB 5 ==> 1 Pulse / RUB 10
 Reject RUB 5 AND RUB 10==> 1 Pulse / RUB 50

L77F/PL77-RUB7(Pulse/RS232 A0/ccNet/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
RS232 A0 Mode		ON	ON	
★ Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

FUNCTION	SW1	SW2	SW3	SW4
Baud rate 19200	ON			
★ Baud rate 9600	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

Currency Assign Data

Interface	Pulse	ICT104U	ccNet	RS232 A0
Bill value				
BV1	RUB 10	RUB 10	RUB 10	RUB 10
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	Reserved	Reserved	Reserved	Reserved
BV7	RUB 200	RUB 200	RUB 200	RUB 200
BV8	Reserved	Reserved	Reserved	Reserved
BV9	RUB 5	RUB 5	RUB 5	RUB 5

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
★ ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
★ RS232 A0 Mode		ON	ON	
Pulse Mode		ON	OFF	
ccNet Mode		OFF	OFF	
ICT104U Mode		OFF	ON	
Reserved				ON
★				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	RUB 200
2	RUB 2000
3	RUB 10
4	RUB 50
5	RUB 100
6	RUB 500
7	RUB 1000
8	RUB 5000
9	RUB 5