

## L83-BAM10(BAM5+EUR5)

### L83 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill **BAM 10, 20, 50, 100, 200 5bills.**  
**EUR 5, 10, 20, 50, 100 5bills.**

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / BAM 10 & EUR 5	OFF	OFF	OFF							
2 Pulses / BAM 10 & EUR 5	OFF	OFF	ON							
3 Pulses / BAM 10 & EUR 5	OFF	ON	OFF							
4 Pulses / BAM 10 & EUR 5	OFF	ON	ON							
5 Pulses / BAM 10 & EUR 5	ON	OFF	OFF							
10 Pulses / BAM 10 & EUR 5	ON	OFF	ON							
20 Pulses / BAM 10 & EUR 5	ON	ON	OFF							
100 Pulses / BAM 10 & EUR 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept BAM 10 & EUR 5						ON				
Reject BAM 10 & EUR 5						OFF				
★ Accept BAM 20 & EUR 10							ON			
Reject BAM 20 & EUR 10							OFF			
★ Accept BAM 50 & EUR 20								ON		
Reject BAM 50 & EUR 20								OFF		
★ Accept BAM 100,200 & EUR 50,100									ON	
Reject BAM 100,200 & EUR 50,100									OFF	
★ Accept BAM+EUR										ON
Accept BAM Only										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L83-BAM10(BAM5+EUR5)(Pulse/ICT104U/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
ICT104U Interface		OFF	ON	
★ MDB Mode		ON	ON	
Reserved				ON
★				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB
BV1	BAM 10	BAM 10	BAM 10
BV2	BAM 20	BAM 20	BAM 20
BV3	BAM 50	BAM 50	BAM 50
BV4	BAM 100	BAM 100	BAM 100
BV5	BAM 200	BAM 200	BAM 200
BV6	EUR 5	EUR 5	EUR 5
BV7	EUR 10	EUR 10	EUR 10
BV8	EUR 20	EUR 20	EUR 20
BV9	EUR 50	EUR 50	EUR 50
BV10	EUR 100	EUR 100	EUR 100