

NK77-LAK8

NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT104U)

Supported bill LAK 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 8bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / LAK 500	OFF	OFF									
	2 Pulses / LAK 500	OFF	ON									
	5 Pulses / LAK 500	ON	OFF									
	10 Pulses / LAK 500	ON	ON									
★	Enable Fish Stop			ON								
	Disable Fish Stop			OFF								
★	Inhibit level Active Low				ON							
	Inhibit level Active High				OFF							
★	Accept LAK 500 & 1000 & 2000 & 5000					ON						
	Reject LAK 500 & 1000 & 2000 & 5000					OFF						
★	Accept LAK 10000 & 20000 & 50000 & 100000						ON					
	Reject LAK 10000 & 20000 & 50000 & 100000						OFF					
	Enable Output Sensor Detect							ON				
★	Disable Output Sensor Detect							OFF				
★	Pulse Normal High								ON			
	Pulse Normal Low								OFF			
★	Pulse Mode									ON		
	ICT104U Mode									OFF		
★	Power On Motor Plus										ON	
	Power On Motor Minus										OFF	

(★) Manufacture setting

Note:(1) Please reset the bill acceptor after set the dip switch.

(2) Pulse mode has out of service function.

(3) Out of service: Normal High, Error Low.

(4) Pulse speed is LO=50ms/HI=100ms

Currency Assign Data

Interface Bill value	ICT104U		Pulse	
BV1	LAK	500	LAK	500
BV2	LAK	1000	LAK	1000
BV3	LAK	2000	LAK	2000
BV4	LAK	5000	LAK	5000
BV5	LAK	10000	LAK	10000
BV6	LAK	20000	LAK	20000
BV7	LAK	50000	LAK	50000
BV8	LAK	100000	LAK	100000