

V7P-RUB7

V7P Option Switch Settings: 1(Pulse/ICT104/ICT104U/MDB)

Supported bill Ruble 50, 100, 200, 500, 1000, 2000, 5000 7bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 50 & 100	ON											
★	Accept Ruble 50 & 100	OFF											
★	Reject Ruble 200		ON										
★	Accept Ruble 200		OFF										
★	Reject Ruble 500 & 1000			ON									
★	Accept Ruble 500 & 1000			OFF									
★	Reject Ruble 2000				ON								
★	Accept Ruble 2000				OFF								
★	Reject Ruble 5000					ON							
★	Accept Ruble 5000					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Ruble 50									OFF	OFF		
★	2 pulses / Ruble 50									ON	OFF		
★	5 pulses / Ruble 50									OFF	ON		
★	10 pulses / Ruble 50									ON	ON		
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

V7P-RUB7(Pulse/ICT104/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104 Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104 Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104 Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104	MDB	Pulse
BV1				
BV2	Ruble 50	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000	Ruble 1000
BV6	Ruble 5000	Ruble 5000	Ruble 5000	Ruble 5000
BV7	Ruble 200	Ruble 200	Ruble 200	Ruble 200
BV8	Ruble 2000	Ruble 2000	Ruble 2000	Ruble 2000

Interface Settings: 2(ICT104)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ICT104 Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting