

L70+/L70F-ZAR5

L70/P5 DIP SWITCHES SETTING : 1(ICT104U/Pulse)

Supported bill ZAR 10, 20, 50, 100, 200 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / ZAR 10	OFF	OFF	OFF							
	2 Pulses / ZAR 10	OFF	OFF	ON							
	3 Pulses / ZAR 10	OFF	ON	OFF							
	4 Pulses / ZAR 10	OFF	ON	ON							
	5 Pulses / ZAR 10	ON	OFF	OFF							
	10 Pulses / ZAR 10	ON	OFF	ON							
	20 Pulses / ZAR 10	ON	ON	OFF							
	100 Pulses / ZAR 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept ZAR 10				ON						
	Reject ZAR 10				OFF						
★	Accept ZAR 20				ON						
	Reject ZAR 20				OFF						
★	Accept ZAR 50				ON						
	Reject ZAR 50				OFF						
★	Accept ZAR 100				ON						
	Reject ZAR 100				OFF						
★	Accept ZAR 200				ON						
	Reject ZAR 200				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+/L70F - ZAR5(ICT104U/Pulse)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	ZAR 10	ZAR 10
BV2	ZAR 20	ZAR 20
BV3	ZAR 50	ZAR 50
BV4	ZAR 100	ZAR 100
BV5	ZAR 200	ZAR 200

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

★ Manufacture setting